

This package contains upgrade data dedicated to owners of Irdeto 1.06 Eurocams (Softcell 2.09) wishing to update them into Irdeto 1.10 version (Softcell 2.21a).



<<< PART NUMBER OF MODULES SUBJECT TO THAT  
UPGRADE IS : **P/N: 901275 ONLY** >>>

**!! PLEASE CHECK ON BOTTOM LABEL OF YOUR IRDETO  
MODULE!!**

### Equipment required for the update

Enclosed update material is usable on PCs running with Windows 95 or Windows 98 operating systems only, featuring a PCMCIA slot.

*Windows NT, Windows 2000 and Windows XP operating systems are not supported by the tool provided.*

### Preparation of files

Create a temporary directory and unzip the following files to that destination :

- xaload11.exe
- g110\_11b.out

Then unzip both `eurocam95.inf` and `eurocam98.inf` files into the following directory :  
`c:\windows\inf\`

### Update procedure

1. Start an MS-DOS session;
2. Prompt to the temporary directory that was created during preparation phase;
3. Insert the Irdeto 1.06 Eurocam module in the PCMCIA slot of the PC and wait for beep (beep means that module was recognized);
4. Type `xaload11 g110_11b.out`  
Blocks will start running (two pages of data), up to the final `UPDATE SUCCESSFUL` message.

Once done, extract your module, it is now updated with 1.10 version of Irdeto. It can be checked by browsing in the Irdeto module menu that Module Information contains the right version.

### Remark :

If your PC does not beep when inserting the module, that means that module was not recognized by the PCMCIA controller of the PC. It is unlikely that update will succeed with that hardware combination. Please try with another PC.